

5.6 kVA

PowerPact™ Residential Standby Generator Air-Cooled Gas Engine

INCLUDES:

- True Power™ Electrical Technology
- Digital LED Controller
- Rugged Galvaneal Steel Rust Resistant Sound Attenuated Enclosure
- External Main Circuit Breaker and Control Panel Access
- Flexible Fuel Line Connector
- Composite Mounting Pads
- Natural Gas or LP Gas Operation
- 3 Year Limited Warranty
- UL 2200 Listed
- Capability to be installed within 18" (457 mm) of a building*

Power Rating
Model 006520-0 (Steel - Bisque) - 5.6 kVA 50 Hz



*Only if located away from doors, windows and fresh air intakes, and unless otherwise directed by local codes.

*Built in the USA using domestic and foreign parts

FEATURES

- **INNOVATIVE DESIGN & PROTOTYPE TESTING** are key components of GENERAC'S success in "IMPROVING POWER BY DESIGN." But it doesn't stop there. Total commitment to component testing, reliability testing, environmental testing, destruction and life testing, plus testing to applicable CSA, NEMA, EGSA, and other standards, allows you to choose GENERAC POWER SYSTEMS with the confidence that these systems will provide superior performance.
- **TEST CRITERIA:**
 - ✓ PROTOTYPE TESTED
 - ✓ NEMA MG1-22 EVALUATION
 - ✓ SYSTEM TORSIONAL TESTED
 - ✓ MOTOR STARTING ABILITY
- **POWERPACT™:** Offers an extreme value for those who desire automatic backup power at the most affordable price.
- **SINGLE SOURCE SERVICE RESPONSE** from Generac's dealer network provides parts and service know-how for the entire unit, from the engine to the smallest electronic component.

PowerPact™ System - 5.6 kVA

features and benefits

Engine

- Generac OHV engine A durable, reliable powertrain for maximum power output.
- Cast iron cylinder walls Rigid construction and added durability provide long engine life.
- Low oil level shutdown system Shutdown protection prevents catastrophic engine damage due to low oil.
- High temperature shutdown Prevents damage due to overheating.

Generator

- Revolving field Allows for a smaller, light weight unit that operates 25% more efficiently than a revolving armature generator.
- Skewed stator Produces a smooth output waveform for compatibility with sensitive electronic equipment, with less than 5% THD (total harmonic distortion).
- Displaced phase excitation Maximizes motor starting capability.
- Automatic voltage regulation Regulates the output voltage to $\pm 5\%$ prevents damaging voltage spikes.
- UL 2200 listed For your safety.

Digital Controls

- Multiple LED annunciation Provides specific system information without having to open the generator enclosure.
- Auto/Off/Manual buttons Select the operating mode.
- Utility voltage sensing Constantly monitors utility voltage, setpoints 65% dropout, 80% pick-up, of standard voltage.
- Utility interrupt delay Prevents nuisance start-ups of the engine, setpoint approximately 5 seconds.
- Engine warm-up Ensures engine is ready to assume the load, setpoint approximately 30 seconds.
- Engine cool-down Allows engine to cool prior to shutdown, setpoint approximately 1 minute.
- Seven day exerciser Operates engine to prevent oil seal drying and damage between power outages.
- Smart battery charger Maintains battery charge level to ensure starting.
- Main line circuit breaker Protects generator from overload.
- Multiple protection features Prevents additional damage from occurring within the generator if a fault condition arises.

Unit

- UL weather protective enclosure Sound attenuated enclosure ensures quiet operation and protection against mother nature. Three panels are removable for easy service and maintenance access.
- Enclosed critical grade muffler Quiet, critical grade muffler is mounted inside the unit to prevent injuries.
- Small, compact, attractive Makes for an easy, eye appealing installation, as close as 18" away from a building.*.

Installation System

- 1 ft (305 mm) flexible fuel line connector Absorbs any generator vibration when connected to rigid pipe.
- Composite mounting pads Eliminates the need to pour a concrete pad unless required by local municipalities.

PowerPact™ System - 5.6 kVA

Generator

| | |
|--|--|
| Model | 006520-0 |
| Rated Maximum Continuous Power Capacity (LP) | 5600 VA |
| Rated Maximum Continuous Power Capacity (NG) | 5000 VA |
| Rated Voltage | 220 |
| Rated Maximum Continuous Load Current – 220 Volts | 25.5 / 22.7 |
| Main Line Circuit Breaker | 32 Amp |
| Phase | 1 |
| Number of Rotor Poles | 2 |
| Rated AC Frequency | 50 Hz |
| Power Factor | 1.0 |
| Battery Requirement (not included) | Group U1, 12 Volts and 300 CCA Minimum |
| Unit Weight (lb/kg) | 330/150 |
| Dimensions (L x W x H) in./mm | 36 x 27 x 25/915 x 676 x 640 |
| Sound output in dB(A) at 23 ft (7 m) with generator operating at normal load** | 67 |

Engine

| | |
|---------------------|--|
| Type of Engine | GENERAC OHV |
| Number of Cylinders | 1 |
| Displacement | 420 cc |
| Cylinder Block | Aluminum w/ Cast Iron Sleeve |
| Valve Arrangement | Overhead Valve |
| Ignition System | Solid-state w/ Magneto |
| Governor System | Mechanical |
| Starter | 12 VDC |
| Oil Capacity | Approx. 1.2 qt/1.1 L |
| Operating rpm | 3000 |
| Fuel Consumption | |
| Natural Gas | ft ³ /hr (m ³ /hr) |
| | 1/2 Load |
| | Full Load |
| Liquid Propane | ft ³ /hr (gal/hr) [l/hr] |
| | 1/2 Load |
| | Full Load |

Note: **Fuel pipe must be sized for full load.** Required fuel pressure to generator fuel inlet at all load ranges - 5-7" water column (6-13 mm mercury) for natural gas, 10-12" water column (19-22 mm mercury) for LP gas. For Btu content, multiply ft³/hr x 2500 (LP) or ft³/hr x 1000 (NG). For megajoule content, multiply m³/hr x 93.15 (LP) or m³/hr x 37.26 (NG).

Controls

| | |
|---|---|
| LED Indicators | Simple user interface for ease of operation. |
| Mode Switch: Auto | Automatic Start on Utility failure. 7 day exerciser. |
| Off | Stops unit. Power is removed. Control and charger still operate. |
| Manual/Test (start) | Start with starter control, unit stays on. If utility fails, transfer to load takes place. |
| Engine Start Sequence | Cyclic cranking: Engine cranks a maximum of five times at factory set intervals and durations |
| Engine Warm-up | 30 sec |
| Engine Cool-Down | 1 min |
| Starter Lock-out | Starter cannot re-engage until 5 sec after engine has stopped. |
| 2.5 Amp Smart Battery Charger | Standard |
| Automatic Voltage Regulator | Standard |
| Automatic Low Oil Level Shutdown | Standard |
| Overspeed Shutdown | Standard |
| Underspeed Shutdown | Standard |
| High Temperature Shutdown | Standard |
| Overcrank Protection | Standard |
| Safety Fused | Standard |
| Wiring Error Detection | Standard |
| Battery Problem Warning | Standard |
| Charger Problem Warning | Standard |
| RPM Sensor Loss Shutdown | Standard |
| Maintenance Indicators (Indicate Break-in and Regular Maintenance is due) | Standard |

**Sound levels are taken from the front of the generator. Sound levels taken from other sides of the generator may be higher depending on installation parameters. Rating definitions - Standby: Applicable for supplying emergency power for the duration of the utility power outage. No overload capability is available for this rating. (All ratings in accordance with BS5514, ISO3046 and DIN6271). * Maximum wattage and current are subject to and limited by such factors as fuel Btu/megajoule content, ambient temperature, altitude, engine power and condition, etc. Maximum power decreases about 3.5 percent for each 1,000 feet (304.8 meters) above sea level; and also will decrease about 1 percent for each 6 °C (10 °F) above 16 °C (60 °F).

PowerPact™ System - 5.6 kVA
available accessories

| Model # | Product | Description |
|----------|---------------------------|--|
| 006882-0 | Cold Weather Kit | The cold weather kit is required for PowerPact units installed in regions where the temperature regularly falls below 32 °F (0 °C). |
| 006806-0 | Scheduled Maintenance Kit | Generac's scheduled maintenance kits provide all the hardware necessary to perform complete routine maintenance on a Generac automatic standby generator. |
| 005703-0 | Paint Kit | If the generator enclosure is scratched or damaged, it is important to touch-up the paint to protect from future corrosion. The paint kit includes the necessary paint to properly maintain or touch-up a generator enclosure. |
| 006664-0 | Local Wireless Remote | Completely wireless and battery powered, Generac's wireless remote monitor provides you with instant status information without ever leaving the house. |

dimensions & UPC

Dimensions shown are approximate. Refer to installation manual for exact dimensions. DO NOT USE THESE DIMENSIONS FOR INSTALLATION PURPOSES.

